

ACE Emergency Lighting Inverters Power Table

Rated Fixture Power (W)	Maximum Number of Fixtures that can be connected to the Inverter*							
	ACI-H7-A1	ACI-H10-A1	ACI-H25-A1	ACI-H35-A1	ACI-H50-A1	ACI-H80-A1	ACI-H100-A1	ACI-H250-A1
3	11	16						
4	8	12						
5	7	10	25	35				
6	5	8	20	29				
7	5	7	17	25				
8	4	6	15	21				
9	3	5	13	19				
10	3	3	12	17	25			
11	3	4	11	15	22			
12	2	4	10	14	20			
13	2	3	9	13	19			
14	2	3	8	12	17			
15	2	3	8	11	16			
16	2	3	7	10	15			
17	2	2	7	10	14			
18	1	2	6	9	13			
19	1	2	6	9	13			
20	1	2	6	8	12	20		
25	1	2	5	7	10	16	20	
30	1	1	4	5	8	13	16	33
35	1	1	3	5	7	11	14	28
40	1	1	3	4	6	10	12	25
45		1	2	3	5	9	11	22
50		1	2	3	5	8	10	20
60				2	4	6	8	16
70				2	3	5	7	14
80				2	3	5	6	12
90				1	2	4	5	11
100				1	2	4	5	10
125				1	2	3	4	8
175				1	1	2	2	5
200					1	2	2	5
240					1	2	2	4
250					1	2	2	4

Note: For details, please see the individual ACE Inverter Automatic Power Share tables 2.

**For questions or to place an order contact us at oemsales@aceleds.com or 800-375-6355
or your local WPG Americas Sales representative at inquiry@wpgamericas.com or 888-WPC8881**